

Substitute Specification:

**-- METHOD AND APPARATUS FOR FAULT REVERSION  
IN A COMMUNICATIONS SYSTEM SWITCHING DEVICE**

**BACKGROUND OF THE INVENTION**

Field of the Invention:

The present invention pertains to a method and apparatus for reversion of a fault in an active peripheral assembly of a switching device in a communications system. In particular, the present invention pertains to a method and apparatus for reversion of a fault in an active peripheral assembly of a switching device in an ATM (Asynchronous Transfer Mode) communications system.

Discussion of the Related Art:

It is known in switching devices of communications systems for communications links to be switched via peripheral assemblies of a switching device, that is to say to handle the communications links with the aid of hardware components of the peripheral assemblies, in particular to set up, to maintain and to end such links. Furthermore, it is known for a number of peripheral assemblies to be controlled via a central switching-internal computer. The central computer transmits, in particular, signals relating to the setting up and clearing of communications links, to the peripheral assemblies.

From ATM communications technology, it is known for permanent and signaled communications links to be set up and to be maintained. The permanent communications links are normally set up and maintained over

09/763033-00504

lengthy time periods by the operator of a communications system. Permanent communications links are subject to particularly stringent reliability requirements.

Signaled communications links are produced on request by the operator or by a user of the communications system and, as a rule, are maintained for shorter time periods than the permanent communications links. For example, a signaled communications link is ended when a telephone handset is placed on the rest. A typical feature of a signaled communications link is that it is left to the communications system to decide which chain of a number of possible physical path elements for transmission of communications signals will be set up for the signaled communications link.

Furthermore, it is known for signaled permanent communications links to be set up and maintained over a similarly lengthy time period as permanent communications links. Signaled permanent communications links are subject to similarly stringent reliability requirements as are permanent communications links. In contrast to permanent communications links, the operator or a user of a signaled permanent communications link communications system specifies only some of the nodes in the communications system and/or only some of the physical transmission sections, via which the communications link is intended to be set up.

Apart from this, setting up of a signaled permanent communications link is left to the communications system. As in the case of signaled communications links, signaled permanent communications links require additional connection data and/or connection data of a different type to be stored, in comparison with

the data for permanent communications links, in order to handle the communications links.

In order to allow faults in an active peripheral assembly to be reversed, redundant peripheral assemblies and/or redundant transmission paths need to be provided. If a peripheral assembly or a transmission path fails, the communications link or links are routed to the redundant peripheral assembly and/or transmission path. In this case, a distinction is drawn between different types of redundancy. For example, peripheral assemblies may have so-called 1+1 redundancy or 1:N redundancy.

In the case of 1+1 redundancy, a passive peripheral assembly is provided for an individual active peripheral assembly and is available exclusively as a standby assembly for that active peripheral assembly. In consequence, the passive, redundant assembly may contain essentially the same hardware and software settings as the active assembly. In practice however, the software settings in particular, such as connection data stored in the assembly, change at short time intervals. The software for the passive, redundant assembly is thus not reliably at the latest standard, so that it is not possible to switch over from the active assembly to the passive assembly without updating the software and/or the connection data.

Furthermore, there is no assurance that the same hardware settings would exist at the same time in both assemblies. For this reason, loss of all the signaled communications links must be expected if it is also possible for some of these signaled communications links to be maintained.

Therefore, when switching over from an active transmission path to a 1+1 redundant transmission path, it may be necessary to switch a number of peripheral assemblies which each have 1+1 redundancy. This increases the probability that the majority, or all the signaled communications links, will be lost. In the case of 1:N redundancy, there is only one joint redundant assembly where the number of assemblies is  $N > 1$ . Presets in the redundant assembly, which speed up switching from one of the N active assemblies to the redundant assembly, which ensure that existing signaled communications links are maintained, thus cannot be carried out, or can be carried out only to a limited extent, according to the known method.

When software faults occur in an active peripheral assembly, the entire assembly may need to be reset and restarted. In the process, all the connection data for signaled communications links are deleted, so that all these communications links are terminated.

### **SUMMARY OF THE INVENTION**

It is an object of the invention to provide a method and apparatus for reversion of a fault in a communications system.

It is another object of the invention to provide a method and apparatus in which stable signaled communications links in a communications system can be reliably maintained after the occurrence of a fault.

05763033 021504

It is a further object of the invention to provide a method and apparatus for specifying a corresponding switching device in a communications system after the occurrence of a fault.

It is an additional object of the invention to provide a method and apparatus in an ATM (Asynchronous Transfer Mode) communications system in which at least one signaled communications link is switched via an active peripheral assembly after the occurrence of a fault.

It is yet another object of the invention to provide a method and apparatus in which connection data for communications link on a communications system are stored in an active peripheral assembly.

It is yet a further object of the invention to provide a method and apparatus for an ATM communications system having a central control unit and a number of associated peripheral assemblies via which communications links can be switched.

### **BRIEF DESCRIPTION OF THE DRAWINGS**

Figure 1 shows a switching device according to the present invention.

### **DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS**

Figure 1 shows a switching device EXC having two 1+1 redundant interface assemblies according to the present invention.

The switching device EXC has two interface assemblies LIC1, LIC2 which are 1+1 redundant with respect to one another. A large number of



data are copied to a volatile memory, for example a RAM, which contains the database CDB.

The method steps of the present invention for reversion of a fault in an active peripheral assembly LIC1 or LIC2 of a switching device EXC in a communication system include, switching at least one signaled communications link via the active peripheral assemblies LIC1, LIC2, storing connection data for the communications link in the active peripheral assemblies LIC1, LIC2 in order to handle the communications link, and transmitting to the active peripheral assemblies LIC1, LIC2 connection data stored in a switching data manager RHS after occurrence of the fault.

The data manager RHS is central to a number of peripheral assemblies LIC1, LIC2, and the connection data held by the memory devices RHS is stored in a redundant manner.

According to the method of the present invention, transmission of the connection data can be interrupted or started at a later time, in order to allow the setting up of new communications links.

Data is transmitted from permanent communications links to the interface assembly LIC2 which are stored in a redundant manner in the central switching computer MP. Hardware settings relating to the connection hardware ASIC of the interface assembly LIC2 can be checked for consistency with the data of the permanent communications links, and for any corrections which may be necessary to the hardware settings to be carried out. The connection manager

COH of the interface assembly LIC2 is involved in this activity, in that it reads the data from the database CDB and carries out the appropriate test steps.

Connection data, which are stored in a redundant manner in the central switching computer MP, for the signaled communications links are transmitted to the interface assembly LIC2, which is being or has been maintained with the aid of the connection hardware ASIC in the interface assembly LIC2.

In the process, it is possible for individual signaled communications links, or for a number of signaled communications links, to be interrupted or terminated as a result of the fault which has occurred. A switching data manager RHS in the central switching computer MP transmits the connection data for the signaled communications links to the connection manager COR in the interface assembly LIC2. In the process, the connection data are transmitted in data blocks of predetermined length. It takes the connection manager COH a period of 5ms, for example, to receive a data block, with connection data being received for about 30 signaled communications links for the interface assembly LIC2.

After reception of the data block, the connection manager COH starts to check the hardware settings of the corresponding communications links, which are carried out in the connection hardware ASIC. It takes the connection manager COH, for example, about half a second to read the connection data and to check them for consistency with the hardware settings for about 30 communications links.

The connection manager COH is informed by the connection data manager RHS when a request to set up a new communications link is present in



the central switching computer MP. Before the transmission of the first data block, or between the transmission of two data blocks, the connection manager COH reacts to the request by setting up a new communications link on the basis of the connection data which it receives from the data manager RHS together with the information about the presence of the request.

The new communications link may be a signaled communications link or a non-signaled communications link. Corresponding procedures are used in the presence of requests to set up a number of new communications links. In this case, the corresponding data can be transmitted individually or in blocks to the connection manager COH. The requests for new communications links preferably have priority over the checking of the hardware settings of already existing communications links, so that they are processed with priority by the connection manager COH. Furthermore, however, a time interval of predetermined length is preferably provided after which, at the latest, the connection manager COH again receives connection data from existing communications links, or continues with checking the hardware settings of communications links whose connection data it already has. During operation of communications systems in practice, it is accepted that the setting up of requested new communications links in a peripheral assembly will be delayed by around 500ms.

As described above, the connection data for approximately 30 already existing communications links can be read and the corresponding hardware settings checked within 500ms. The checking of the hardware setting is

annotated in Figure 1 by the reference symbol d, and the resetting of communications links in the connection hardware HSIC is annotated by the reference symbol d'.

Before, during and after reception of connection data for already existing communications links and/or reception of connection data of communications links to be set up as new, a start pulse for a time-interval measurement for connection-duration-dependent charges is in case issued, in a development of the invention. If the connection manager COH has the respective connection data for such a communications link, it sends the start pulse to the charge meter TM which is provided in the interface assembly LIC2. The transmission of the charge-meter start pulse for already existing communications links is illustrated as method step c, and the corresponding transmission of a start pulse for a communications link which is to be set up as new is shown as method step c'.

In another embodiment described with reference to Figure 1, the central switching computer MP transmits a request to the connection manager CON to terminate an existing communications link.

However, the charge-meter start pulse according to method step c has not yet been transmitted from the connection manager CON to the charge meter TM at this time. The connection manager COH thus does not confirm the request, and does not act on this request either. This ensures that the charge meter TM can determine the connection-duration-dependent charges correctly and does not receive a charge-meter stop pulse before receiving a charge-meter start pulse for an existing communications link. Since the central switching computer

MP have not received any confirmation from the connection manager COH, it repeats the transmission of the request to terminate the communications link, preferably at time intervals which are fixed in advance. In the meantime, for example between the first and the third transmission of the request, the connection manager COH will have received the connection data for the relevant communications link, and will have sent a corresponding charge-meter start pulse to the charge meter TM.

This acknowledges the third request with a confirmation, sends a charge-meter stop pulse to the charge meter TM, and terminates the communications link by making appropriate hardware settings in the connection hardware ASIC.

In the embodiments described so far, it has been assumed that there has been a software fault in the interface assembly LIC2. The same method, together with its development can be applied, for example, to a situation in which a hardware fault has occurred in the previously active interface assembly LIC1 and the 1+1 redundant interface assembly LIC2 has taken over the active function from the interface assembly LIC1. Furthermore, the method can be used in situations in which there is no redundant component or in which 1:N redundancy exists. Overall, a universal method is thus available for reversion of a fault in an active peripheral assembly in a switching device, which allows all those communications links which are stable after the occurrence of the fault to be maintained while having to accept, at worst, only short interruption times. Furthermore, the universal method ensures the setting up of communications

links as new with the least possible time delay while reliably deleting all possibly faulty data in the assembly.

According to the present invention, connection data for at least one communications link, which data are stored in the active peripheral assembly, are also stored elsewhere in a redundant manner. After the occurrence of the fault, the connection data which are stored elsewhere in a redundant manner are used in order to continue to handle the communications link. Storage of two up-to-date sets of connection data ensures that the connection data are still available, at least once, after the failure or after the occurrence of the fault in the active peripheral assembly. Provided the redundant set of connection data, or at least one of the redundant sets of connection data, is or are undamaged after the occurrence of the fault, the undamaged data set can be used to continue to handle the communications link.

It is thus possible to maintain the at least one signaled communications link, provided it is still stable after the occurrence of the fault. In order to preclude the possibility of the set of data which is stored in the faulty peripheral assembly being damaged and thus endangering the maintenance of the at least one communications link when it is used further, the connection data stored in the faulty peripheral assembly are preferably deleted.

According to the present invention, signaled communications links can be maintained with the same reliability as permanent communications links, which may be unstable in the same way as the signaled communications links after the occurrence of the fault, or can no longer be maintained owing to the fault.

The present invention can also be used in other communications system, for example in STM (Synchronous Transfer Mode) communications systems.

The term peripheral assembly means an assembly or unit of a switching device which is directly involved in the setting up and/or in the maintenance of a communications link. The term peripheral assemblies covers, in particular, interface assemblies (Line Interface Cards LIC), which form an interface to transmission lines outside the switching system, multiplexer units (for example Statistical Multiplexing Units SMU) which connect a number of interface assemblies to a switching network, switching networks (ATM Switching Networks ASN) which produce the correct output from a number of possible outputs in response to signals arriving at them. In particular, the assemblies have a large number of elements which carry out functions on the assembly, but at least a memory area for storing the connection data and an element which is directly involved in the communications link.

In a communications system, the term switching device means a device which allows various switching-system-external and/or switching-system-internal transmission paths or transmission lines to be connected to one another or to be enabled for the purposes of setting up a communications link.

The term communications link means a link for connection of any desired type via which signals can be transmitted within the communications system or beyond the boundaries of the communications system.

The connection data are preferably stored in a memory device which is central for the number of peripheral assemblies, before the fault occurs. In

particular, the memory device is part of a central switching computer of the switching device. In this case, the switching computer may, for example, update that copy of the connection data which is stored in its memory device whenever it informs the active peripheral assembly of changes which relate to the connection data.

However, the central memory for the connection data for a number of peripheral assemblies has the advantage that one common memory unit or memory device is sufficient, and that the data administration can be carried out in an effective manner.

In one development, a redundant passive peripheral assembly, in which the connection data are stored in a redundant manner, is provided for the active peripheral assembly. In contrast to the prior art, the passive peripheral assembly is used to store a set of connection data which is just as up-to-date as that in the active peripheral assembly. This firstly creates the possibility simply of switching over to the passive peripheral assembly after the occurrence of the fault in the active peripheral assembly while, on the other hand, it is possible to transmit the connection data from the passive peripheral assembly to the active peripheral assembly, for example if the connection data stored in the active peripheral assembly are faulty, or there is a possibility of such data being faulty.

If a fault occurs in the software of the active peripheral assembly, the connection data which are stored elsewhere in a redundant manner can be transmitted, in a preferred manner, to the peripheral assembly which is still active after the occurrence of the fault. Faults in software covers not only faults in

programs, but also faults in stored data to which access can be made while a program is running.

In many fault situations, continuation of operation of the active peripheral assembly represents the fastest and most reliable option for maintaining stable communications links without considerable interruptions. Mostly, hardware settings still exist in the active peripheral assembly in order to maintain a communications link after the occurrence of the fault. This is preferably checked after the transmission of the connection data stored elsewhere in a redundant manner, or at least after transmission of some of these connection data items.

During the check it is also, for example, possible to confirm whether the connection data stored elsewhere in a redundant manner have been changed as a consequence of their having been updated in the meantime, so that corresponding corrections or changes are required to the hardware settings. One possible reason for this occurs when a message that the communications link is intended to be ended arrives at a central switching computer in the meantime.

Connection data to be transmitted remains stored at the other location, that is to say they are transmitted in the form of a copy. This also applies to situations in which, after the occurrence of the fault, previously active peripheral assembly become passive and a redundant assembly is used as the active peripheral assembly, to which the connection data stored elsewhere in a redundant manner are transmitted. Thus, it is possible to maintain stable

communications links in particular when hardware faults occur in the previously active peripheral assembly.

Transmission of the connection data to the peripheral assembly which is active after the occurrence of the fault is interrupted, or is not started until later, in order to allow the setting up of new communications links. In this case, expediently, the connection data to be transmitted are transmitted in blocks to the active peripheral assembly. One major advantage of this development is that, as soon as it is confirmed which peripheral assembly will be taking over or continuing the active operation after the occurrence of the fault, new communications links can be set up, and in this case it is possible to use the same method as that for fault-free operation.

The fault reversion according to the present invention can also be carried out in a corresponding manner for other types of peripheral assemblies for a switching device.

With regard to the apparatus, the central control unit of the switching device has a data memory in which connection data can be stored from signaled subscriber connections which are switched via the associated peripheral assemblies, and in that a transmission unit is provided for reading and transmitting the connection data to the associated peripheral assemblies.

Although modifications and changes may be suggested by those skilled in the art to which this invention pertains, it is the intention of the inventors to embody within the patent warranted hereon all changes and modifications that



may reasonably and properly come under the scope of their contribution to the art. - -

[illegible]